

# Thumb® Instruction Set

## Quick Reference Card

Key to Tables			
<loreglist>	A comma-separated list of Lo registers, enclosed in braces, { and }.	<loreglist+LR>	A comma-separated list of Lo registers, plus the LR, enclosed in braces, { and }.
		<loreglist+PC>	A comma-separated list of Lo registers, plus the PC, enclosed in braces, { and }.

All Thumb registers are Lo (R0-R7) except where specified. Hi registers are R8-R15.

Operation	§	Assembler	Updates	Action	Notes
<b>Move</b>	Immediate	MOV Rd, #<immed>	N Z	Rd := immed	Immediate range 0-255.
	Lo to Lo	MOV Rd, Rm	N Z * *	Rd := Rm	* Clears C and V flags.
	Hi to Lo, Lo to Hi, Hi to Hi	MOV Rd, Rm		Rd := Rm	Not Lo to Lo. Flags not affected.
	Copy Any to Any	6 CPY Rd, Rm		Rd := Rm	Any register to any register. Flags not affected.
<b>Arithmetic</b>	Add	ADD Rd, Rn, #<immed>	N Z C V	Rd := Rn + immed	Immediate range 0-7.
	Lo and Lo	ADD Rd, Rn, Rm	N Z C V	Rd := Rn + Rm	
	Hi to Lo, Lo to Hi, Hi to Hi	ADD Rd, Rm		Rd := Rd + Rm	Not Lo to Lo. Flags not affected.
	immediate	ADD Rd, #<immed>	N Z C V	Rd := Rd + immed	Immediate range 0-255.
	with carry	ADC Rd, Rm	N Z C V	Rd := Rd + Rm + C-bit	
	value to SP	ADD SP, #<immed>		R13 := R13 + immed	Immediate range 0-508 (word-aligned). Flags not affected.
	form address from SP	ADD Rd, SP, #<immed>		Rd := R13 + immed	Immediate range 0-1020 (word-aligned). Flags not affected.
	form address from PC	ADD Rd, PC, #<immed>		Rd := (R15 AND 0xFFFFF) + immed	Immediate range 0-1020 (word-aligned). Flags not affected.
	Subtract	SUB Rd, Rn, Rm	N Z C V	Rd := Rn - Rm	
	immediate 3	SUB Rd, Rn, #<immed>	N Z C V	Rd := Rn - immed	Immediate range 0-7.
	immediate 8	SUB Rd, #<immed>	N Z C V	Rd := Rd - immed	Immediate range 0-255.
	with carry	SBC Rd, Rm	N Z C V	Rd := Rd - Rm - NOT C-bit	
	value from SP	SUB SP, #<immed>		R13 := R13 - immed	Immediate range 0-508 (word-aligned). Flags not affected.
	Negate	NEG Rd, Rm	N Z C V	Rd := - Rm	
Multiply	MUL Rd, Rm	N Z * *	Rd := Rm * Rd	* C and V flags unpredictable in §4T, unchanged in §5T and above	
Compare	CMP Rn, Rm	N Z C V	update CPSR flags on Rn - Rm	Can be Lo to Lo, Lo to Hi, Hi to Lo, or Hi to Hi.	
negative	CMN Rn, Rm	N Z C V	update CPSR flags on Rn + Rm		
immediate	CMP Rn, #<immed>	N Z C V	update CPSR flags on Rn - immed	Immediate range 0-255.	
No operation	NOP		None	Flags not affected.	
<b>Logical</b>	AND	AND Rd, Rm	N Z	Rd := Rd AND Rm	
	Exclusive OR	EOR Rd, Rm	N Z	Rd := Rd EOR Rm	
	OR	ORR Rd, Rm	N Z	Rd := Rd OR Rm	
	Bit clear	BIC Rd, Rm	N Z	Rd := Rd AND NOT Rm	
	Move NOT	MVN Rd, Rm	N Z	Rd := NOT Rm	
	Test bits	TST Rn, Rm	N Z	update CPSR flags on Rn AND Rm	
<b>Shift/rotate</b>	Logical shift left	LSL Rd, Rm, #<shift>	N Z C*	Rd := Rm << shift	Allowed shifts 0-31. * C flag unaffected if shift is 0.
		LSL Rd, Rs	N Z C*	Rd := Rd << Rs[7:0]	* C flag unaffected if Rs[7:0] is 0.
	Logical shift right	LSR Rd, Rm, #<shift>	N Z C	Rd := Rm >> shift	Allowed shifts 1-32.
		LSR Rd, Rs	N Z C	Rd := Rd >> Rs[7:0]	* C flag unaffected if Rs[7:0] is 0.
	Arithmetic shift right	ASR Rd, Rm, #<shift>	N Z C	Rd := Rm ASR shift	Allowed shifts 1-32.
		ASR Rd, Rs	N Z C*	Rd := Rd ASR Rs[7:0]	* C flag unaffected if Rs[7:0] is 0.
Rotate right	ROR Rd, Rs	N Z C*	Rd := Rd ROR Rs[7:0]	* C flag unaffected if Rs[7:0] is 0.	
<b>Reverse</b>	Bytes in word	6 REV Rd, Rm		Rd[31:24] := Rm[7:0], Rd[23:16] := Rm[15:8], Rd[15:8] := Rm[23:16], Rd[7:0] := Rm[31:24]	
	Bytes in both halfwords	6 REV16 Rd, Rm		Rd[15:8] := Rm[7:0], Rd[7:0] := Rm[15:8], Rd[31:24] := Rm[23:16], Rd[23:16] := Rm[31:24]	
	Bytes in low halfword, sign extend	6 REVSH Rd, Rm		Rd[15:8] := Rm[7:0], Rd[7:0] := Rm[15:8], Rd[31:16] := Rm[7] * &FFFF	

Operation	§	Assembler	Action	Notes
<b>Load</b>	with immediate offset, word	LDR Rd, [Rn, #<immed>]	Rd := [Rn + immed]	Immediate range 0-124, multiple of 4.
	halfword	LDRH Rd, [Rn, #<immed>]	Rd := ZeroExtend([Rn + immed][15:0])	Clears bits 31:16. Immediate range 0-62, even.
	byte	LDRB Rd, [Rn, #<immed>]	Rd := ZeroExtend([Rn + immed][7:0])	Clears bits 31:8. Immediate range 0-31.
	with register offset, word	LDR Rd, [Rn, Rm]	Rd := [Rn + Rm]	
	halfword	LDRH Rd, [Rn, Rm]	Rd := ZeroExtend([Rn + Rm][15:0])	Clears bits 31:16
	signed halfword	LDRSH Rd, [Rn, Rm]	Rd := SignExtend([Rn + Rm][15:0])	Sets bits 31:16 to bit 15
	byte	LDRB Rd, [Rn, Rm]	Rd := ZeroExtend([Rn + Rm][7:0])	Clears bits 31:8
	signed byte	LDRSB Rd, [Rn, Rm]	Rd := SignExtend([Rn + Rm][7:0])	Sets bits 31:8 to bit 7
PC-relative	LDR Rd, [PC, #<immed>]	Rd := [(R15 AND 0xFFFFF0) + immed]	Immediate range 0-1020, multiple of 4.	
SP-relative	LDR Rd, [SP, #<immed>]	Rd := [R13 + immed]	Immediate range 0-1020, multiple of 4.	
Multiple	LDMIA Rn!, <reglist>	Loads list of registers	Always updates base register.	
<b>Store</b>	with immediate offset, word	STR Rd, [Rn, #<immed>]	[Rn + immed] := Rd	Immediate range 0-124, multiple of 4.
	halfword	STRH Rd, [Rn, #<immed>]	[Rn + immed][15:0] := Rd[15:0]	Ignores Rd[31:16]. Immediate range 0-62, even.
	byte	STRB Rd, [Rn, #<immed>]	[Rn + immed][7:0] := Rd[7:0]	Ignores Rd[31:8]. Immediate range 0-31.
	with register offset, word	STR Rd, [Rn, Rm]	[Rn + Rm] := Rd	
	halfword	STRH Rd, [Rn, Rm]	[Rn + Rm][15:0] := Rd[15:0]	Ignores Rd[31:16]
	byte	STRB Rd, [Rn, Rm]	[Rn + Rm][7:0] := Rd[7:0]	Ignores Rd[31:8]
	SP-relative, word	STR Rd, [SP, #<immed>]	[R13 + immed] := Rd	Immediate range 0-1020, multiple of 4.
Multiple	STMIA Rn!, <reglist>	Stores list of registers	Always updates base register.	
<b>Push/Pop</b>	Push	PUSH <loreplist>	Push registers onto stack	Full descending stack.
	Push with link	PUSH <loreplist+LR>	Push LR and registers onto stack	
	Pop	POP <loreplist>	Pop registers from stack	
	Pop and return	4T POP <loreplist+PC>	Pop registers, branch to address loaded to PC	
	Pop and return with exchange	5T POP <loreplist+PC>	Pop, branch, and change to ARM state if address[0] = 0	
<b>Branch</b>	Conditional branch	B{cond} label	R15 := label	label must be within -252 to +258 bytes of current instruction. See Table <b>Condition Field</b> on reverse.
	Unconditional branch	B label	R15 := label	label must be within ±2Kb of current instruction.
	Long branch with link	BL label	R14 := address of next instruction, R15 := label	Encoded as two Thumb instructions. label must be within ±4Mb of current instruction.
	Branch and exchange	BX Rm	R15 := Rm AND 0xFFFFF0	Change to ARM state if Rm[0] = 0.
	Branch with link and exchange	5T BLX label	R14 := address of next instruction, R15 := label Change to ARM	Encoded as two Thumb instructions. label must be within ±4Mb of current instruction.
Branch with link and exchange	5T BLX Rm	R14 := address of next instruction, R15 := Rm AND 0xFFFFF0	Change to ARM state if Rm[0] = 0	
<b>Extend</b>	Signed extend halfword to word	6 SXTB Rd, Rm	Rd[31:0] := SignExtend(Rm[15:0])	
	Signed extend byte to word	6 SXTB Rd, Rm	Rd[31:0] := SignExtend(Rm[7:0])	
	Unsigned extend halfword to word	6 UXTH Rd, Rm	Rd[31:0] := ZeroExtend(Rm[15:0])	
	Unsigned extend byte to word	6 UXTB Rd, Rm	Rd[31:0] := ZeroExtend(Rm[7:0])	
<b>Processor state change</b>	Software interrupt	6 SWI <immed_8>	Software interrupt processor exception	8-bit immediate value encoded in instruction.
	Change processor state	6 CPSID <iflags>	Disable specified interrupts	
		6 CPSIE <iflags>	Enable specified interrupts	
	Set endianness	6 SETEND <endianness>	Sets endianness for loads and saves.	<endianness> can be BE (Big Endian) or LE (Little Endian).
	Breakpoint	5T BKPT <immed_8>	Prefetch abort <i>or</i> enter debug state	8-bit immediate value encoded in instruction.

# Vector Floating Point Instruction Set

## Quick Reference Card

<b>Key to Tables</b>	{cond} <S/D> <S/D/X> <VFPsysreg>	See Table <b>Condition Field</b> S (single precision) or D (double precision). As above, or X (unspecified precision). FPSCR, or FPSID.
----------------------	-------------------------------------------	--------------------------------------------------------------------------------------------------------------------------------------------------

Fd, Fn, Fm {E} {Z} <VFPregs>	Sd, Sn, Sm (single precision), or Dd, Dn, Dm (double precision). E : raise exception on any NaN. Without E : raise exception only on signaling NaNs. Round towards zero. Overrides FPSCR rounding mode. A comma separated list of <i>consecutive</i> VFP registers, enclosed in braces ( { and } ).
---------------------------------------	--------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------

Operation	Assembler	Exceptions	Action	Notes													
<b>Vector arithmetic</b>	Multiply	FMUL<S/D>{cond} Fd, Fn, Fm	IO, OF, UF, IX	Fd := Fn * Fm	<table border="1"> <thead> <tr> <th colspan="2">Exceptions</th> </tr> </thead> <tbody> <tr> <td>IO</td> <td>Invalid operation</td> </tr> <tr> <td>OF</td> <td>Overflow</td> </tr> <tr> <td>UF</td> <td>Underflow</td> </tr> <tr> <td>IX</td> <td>Inexact result</td> </tr> <tr> <td>DZ</td> <td>Division by zero</td> </tr> </tbody> </table>	Exceptions		IO	Invalid operation	OF	Overflow	UF	Underflow	IX	Inexact result	DZ	Division by zero
	Exceptions																
	IO	Invalid operation															
	OF	Overflow															
	UF	Underflow															
	IX	Inexact result															
	DZ	Division by zero															
	and negate	FNMUL<S/D>{cond} Fd, Fn, Fm	IO, OF, UF, IX	Fd := - (Fn * Fm)													
	and accumulate	FMAC<S/D>{cond} Fd, Fn, Fm	IO, OF, UF, IX	Fd := Fd + (Fn * Fm)													
	negate and accumulate	FNMAC<S/D>{cond} Fd, Fn, Fm	IO, OF, UF, IX	Fd := Fd - (Fn * Fm)													
	and subtract	FMSC<S/D>{cond} Fd, Fn, Fm	IO, OF, UF, IX	Fd := - Fd + (Fn * Fm)													
negate and subtract	FNMSC<S/D>{cond} Fd, Fn, Fm	IO, OF, UF, IX	Fd := - Fd - (Fn * Fm)														
Add	FADD<S/D>{cond} Fd, Fn, Fm	IO, OF, IX	Fd := Fn + Fm														
Subtract	FSUB<S/D>{cond} Fd, Fn, Fm	IO, OF, IX	Fd := Fn - Fm														
Divide	FDIV<S/D>{cond} Fd, Fn, Fm	IO, DZ, OF, UF, IX	Fd := Fn / Fm														
Copy	FCPY<S/D>{cond} Fd, Fm		Fd := Fm														
Absolute	FABS<S/D>{cond} Fd, Fm		Fd := abs(Fm)														
Negative	FNEG<S/D>{cond} Fd, Fm		Fd := - Fm														
Square root	FSQRT<S/D>{cond} Fd, Fm	IO, IX	Fd := sqrt(Fm)														
<b>Scalar compare</b>	Two values	FCMP{E}<S/D>{cond} Fd, Fm	IO	Set FPSCR flags on Fd - Fm	Use FMSTAT to transfer flags.												
	Value with zero	FCMP{E}Z<S/D>{cond} Fd	IO	Set FPSCR flags on Fd - 0	Use FMSTAT to transfer flags.												
<b>Scalar convert</b>	Single to double	FCVTDS{cond} Dd, Sm	IO	Dd := convertStoD(Sm)													
	Double to single	FCVTSD{cond} Sd, Dm	IO, OF, UF, IX	Sd := convertDtoS(Dm)													
	Unsigned integer to float	FUITO<S/D>{cond} Fd, Sm	IX	Fd := convertUItoF(Sm)													
	Signed integer to float	FSITO<S/D>{cond} Fd, Sm	IX	Fd := convertSIttoF(Sm)													
	Float to unsigned integer	FTOUI{Z}<S/D>{cond} Sd, Fm	IO, IX	Sd := convertFtoUI(Fm)													
	Float to signed integer	FTOSI{Z}<S/D>{cond} Sd, Fm	IO, IX	Sd := convertFtoSI(Fm)													
<b>Save VFP registers</b>		FST<S/D>{cond} Fd, [Rn{, #<immed>}]		[address] := Fd. Immediate range 0-1020, multiple of 4.													
	Multiple, unindexed increment after decrement before	FSTMIA<S/D/X>{cond} Rn, <VFPregs> FSTMIA<S/D/X>{cond} Rn!, <VFPregs> FSTMDB<S/D/X>{cond} Rn!, <VFPregs>		Saves list of VFP registers, starting at address in Rn. synonym: FSTMIA (empty ascending) synonym: FSTMFD (full descending)													
<b>Load VFP registers</b>		FLD<S/D>{cond} Fd, [Rn{, #<immed>}]		Fd := [address]. Immediate range 0-1020, multiple of 4.													
	Multiple, unindexed increment after decrement before	FLDMIA<S/D/X>{cond} Rn, <VFPregs> FLDMIA<S/D/X>{cond} Rn!, <VFPregs> FLDMDB<S/D/X>{cond} Rn!, <VFPregs>		Loads list of VFP registers, starting at address in Rn. synonym: FLDMFD (full descending) synonym: FLDMIA (empty ascending)													
<b>Transfer registers</b>	ARM to single	FMSR{cond} Sn, Rd		Sn := Rd													
	Single to ARM	FMRS{cond} Rd, Sn		Rd := Sn													
	Two ARM to two singles	FMSRR{cond} {Sn,Sm}, Rd, Rn		Sn := Rd, Sm := Rn	Architecture VFPv2 only												
	Two singles to two ARM	FMRRS{cond} Rd, Rn, {Sn,Sm}		Rd := Sn, Rn := Sm	Architecture VFPv2 only												
	Two ARM to double	FMDRR{cond} Dn, Rd, Rn		Dn[31:0] := Rd, Dn[63:32] := Rn	Architecture VFPv2 only												
	Double to two ARM	FMRRD{cond} Rd, Rn, Dn		Rd := Dn[31:0], Rn := Dn[63:32]	Architecture VFPv2 only												
	ARM to lower half of double	FMDLR{cond} Dn, Rd		Dn[31:0] := Rd	Use with FMDHR.												
	Lower half of double to ARM	FMRDL{cond} Rd, Dn		Rd := Dn[31:0]	Use with FMRDH.												
	ARM to upper half of double	FMDHR{cond} Dn, Rd		Dn[63:32] := Rd	Use with FMDLR.												
	Upper half of double to ARM	FMRDH{cond} Rd, Dn		Rd := Dn[63:32]	Use with FMRDL.												
	ARM to VFP system register	FMXR{cond} <VFPsysreg>, Rd		VFPsysreg := Rd	Stalls ARM until all VFP ops complete.												
	VFP system register to ARM	FMRX{cond} Rd, <VFPsysreg>		Rd := VFPsysreg	Stalls ARM until all VFP ops complete.												
	FPSCR flags to CPSR	FMSTAT{cond}		CPSR flags := FPSCR flags	Equivalent to FMRX R15, FPSCR												

# Vector Floating Point Instruction Set

## Quick Reference Card

FPSCR format								Rounding		(Stride - 1)*3		Vector length - 1				Exception trap enable bits						Cumulative exception bits								
31	30	29	28				24	23	22	21	20		18	17	16			12	11	10	9	8				4	3	2	1	0
N	Z	C	V				FZ	RMODE		STRIDE			LEN			IXE	UFE	OFE	DZE	IOE				IXC	UFC	OFC	DZC	IOC		
FZ: 1 = flush to zero mode.								Rounding: 0 = round to nearest, 1 = towards +∞ 2 = towards -∞ 3 = towards zero.						(Vector length * Stride) must not exceed 4 for double precision operands.																

If Fd is S0-S7 or D0-D3, operation is Scalar (regardless of vector length).	If Fd is S8-S31 or D4-D15, and Fm is S0-S7 or D0-D3, operation is Mixed (Fm scalar, others vector).
If Fd is S8-S31 or D4-D15, and Fm is S8-S31 or D4-D15, operation is Vector.	S0-S7 (or D0-D3), S8-S15 (D4-D7), S16-S23 (D8-D11), S24-S31 (D12-D15) each form a circulating bank of registers.

Condition Field		
Mnemonic	Description (Thumb)	Description (VFP)
EQ	Equal	Equal
NE	Not equal	Not equal, or unordered
CS / HS	Carry Set / Unsigned higher or same	Greater than or equal, or unordered
CC / LO	Carry Clear / Unsigned lower	Less than
MI	Negative	Less than
PL	Positive or zero	Greater than or equal, or unordered
VS	Overflow	Unordered (at least one NaN operand)
VC	No overflow	Not unordered
HI	Unsigned higher	Greater than, or unordered
LS	Unsigned lower or same	Less than or equal
GE	Signed greater than or equal	Greater than or equal
LT	Signed less than	Less than, or unordered
GT	Signed greater than	Greater than
LE	Signed less than or equal	Less than or equal, or unordered
AL	Do not use in Thumb	Always (normally omitted)

Exceptions	
IO	Invalid operation
OF	Overflow
UF	Underflow
IX	Inexact result
DZ	Division by zero

## Proprietary Notice

Words and logos marked with ® or ™ are registered trademarks or trademarks owned by ARM Limited. Other brands and names mentioned herein may be the trademarks of their respective owners.

Neither the whole nor any part of the information contained in, or the product described in, this document may be adapted or reproduced in any material form except with the prior written permission of the copyright holder.

The product described in this document is subject to continuous developments and improvements. All particulars of the product and its use contained in this document are given by ARM in good faith. However, all warranties implied or expressed, including but not limited to implied warranties of merchantability, or fitness for purpose, are excluded.

This reference card is intended only to assist the reader in the use of the product. ARM Ltd shall not be liable for any loss or damage arising from the use of any information in this reference card, or any error or omission in such information, or any incorrect use of the product.

## Document Number

ARM QRC 0001H

## Change Log

Issue	Date	By	Change
A	June 1995	BJH	First Release
B	Sept 1996	BJH	Second Release
C	Nov 1998	BJH	Third Release
D	Oct 1999	CKS	Fourth Release
E	Oct 2000	CKS	Fifth Release
F	Sept 2001	CKS	Sixth Release
G	Jan 2003	CKS	Seventh Release
H	Oct 2003	CKS	Eighth Release